

FB5 Ferro-Resonant Battery Charger

Standard Features

- Ferro-Resonant design for maximum reliability
- Negligible input harmonics
- Hi / Low Voltage Alarm (Rectifier Failure)
- AC Fail with indication and Form C relay
- Automatic Equalize after discharge
- AC Breaker 2 Pole for Single phase, 3 Pole for 3 Phase
- Manual Float – Equalize override
- DC Breaker 2 Pole
- DC Ammeter
- DC Voltmeter
- MTBF 120,000 Hours
- Designed for parallel operation with other rectifiers



FB5 FERRO-RESONANT CHARGER

Specifications

Input Voltage:	120, 220, 380, 480, 575, 690, Custom (60 Hz)
Output Voltage:	12, 24, 48, 125, 250, Custom (60 Hz) (1/3ph.)
Regulation:	< 0.5% for input variation of 10%
Short Circuit Protection:	Inherent in Ferro Resonant Design
Enclosure:	NEMA 1
Efficiency:	> 85%
Soft start:	Electronic soft start
Ripple:	2% (1%, 26 dbrnC optional)
Operation:	0-50 Degree Celsius (-40 optional)
Approvals:	CSA, CSA us (UL1012)